

SAL1

配电箱设置层门,内门
开孔预留断路器操作空间。

RS485总线+电源线
RSVP-4*1.0

ZMK

MCB-C16/1P

L1 MCB-C16/2P

+VE 30mA

L2 MCB-C16/2P

+VE 30mA

L3 MCB-C16/2P

+VE 30mA

L1 MCB-C16/2P

+VE 30mA

L2 MCB-C16/2P

+VE 30mA

L3 MCB-C16/2P

+VE 30mA

L1 MCB-C16/2P

+VE 30mA

L2 MCB-C16/2P

+VE 30mA

L3 MCB-C16/2P

+VE 30mA

L1 MCB-C16/2P

WL1 ZR-BV-3x2.5-JDG20-WE,CT 照明

WL2 ZR-BV-3x2.5-JDG20-WE,CT 照明

WL3 ZR-BV-3x2.5-JDG20-WE,CT 照明

WL4 ZR-BV-3x2.5-JDG20-WE,CT 照明

WL5 ZR-BV-3x2.5-JDG20-WE,CT 照明

WL6 ZR-BV-3x2.5-JDG20-WE,CT 照明

WL7 ZR-BV-3x2.5-JDG20-WE,CT 照明

WL8 ZR-BV-3x2.5-JDG20-WE,CT 市电监测

WDZNB2-RYJSP-2x1.5-JDG20
市电监测 至各层照明箱
无源干接点,失电闭合

WP1 ZR-YJV-5x4-JDG25-WC,WE,CT RS

MCB-D20/4P

+VE 30mA

L3 MCB-C20/2P

+VE 30mA

L1 MCB-C20/2P

+VE 30mA

L2 MCB-C20/2P

+VE 30mA

L3 MCB-C20/2P

+VE 30mA

MCB-D20/4P

+VE 30mA

备用

备用

Pe=	20	kW
Kx=	0.9	
Cost=	0.85	
Pjs=	18.0	kW
Ijs=	82.2	A

参考尺寸
WxHxD(mm)
500x600x180
柜高1.5m,明装

1AP3-WP1

MCB-D40/3P

断路器:ASF-R1L1Z 16A.S

