

配电箱设置双层门,内门
开孔预留断路器操作空间。


1ALJCB

检测室

MCB-C32/3P

1AP3:WP9


L1 MCB-C16/2P



WL1 ZR-BV-3x2.5-JDG20-WE,CT

照明


L2 MCB-D20/2P



WX1 ZR-BV-3x4-JDG20-WE,CT

插座


L3 MCB-D20/2P



WX2 ZR-BV-3x4-JDG20-WE,CT

插座


L1 MCB-D20/2P



WX3 ZR-BV-3x4-JDG20-WE,CT

插座


L2 MCB-D20/2P



WX4 ZR-BV-3x4-JDG20-WE,CT

插座


L3 MCB-D20/2P



WX5 ZR-BV-3x4-JDG20-WE,CT

插座


L1 MCB-C16/2P



WK1 ZR-BV-3x2.5-JDG20-WE,CT


空调室内机

L2 MCB-D20/2P



备用

L3 MCB-D20/2P



备用

Pe=	10	kW
Kx=	0.9	
Cosφ=	0.85	
Pjs=	9.0	kW
Ijs=	16.1	A

参考尺寸

=WxHxD(mm)

600x500x180

距地1.5m,暗装